MORNSUN®

E_T-W2 & F_T-W2 Series 0.25W, FIXED INPUT, ISOLATED & UNREGULATED DUAL/SINGLE OUTPUT DC-DC CONVERTER



RoHS

FEATURES

- Small Footprint
- SMD Package Style
- 3KVDC Isolation
- Temperature Range: -40°C ~ +85°C
- No Heatsink Required
- Industry Standard Pinout
- Internal SMD construction
- No External Component Required
- RoHS Compliance

APPLICATIONS

The E_T-W2 & F_T-W2 series are specially designed for applications where a group of polar power supplies are isolated from the input power supply in a distributed power supply system on a circuit board.

These products apply to:

1) Where the voltage of the input power supply is fixed (voltage variation $\leq \pm 10\%$);

 Where isolation is necessary between input and output (isolation voltage ≤3000VDC);

 Where the regulation of the output voltage and the output ripple noise are not demanding.
Such as: purely digital circuits, ordinary low frequency analog circuits, and IGBT power device driving circuits.

MODEL SELECTION

E0505T-W2

	Τ	— Rated Power — Package Style —Output Voltage
L		—Input Voltage
		-Product Series

MORNSUN Science & Technology Co., Ltd.

Address: No. 5, Kehui St. 1, Kehui development center, Science Ave., Guangzhou Science City, Luogang district, Guangzhou,P.R.China. Tel: 86-20-28203030 Fax:86-20-38601272 Http://www.mornsun-power.com

PRODUCT PROGRAM							
_	Input		Output				
Part Number	Voltage (VDC)		Voltage	Current (mA)		Efficiency (%, Tvp.)	
	Nominal	Range	(VDC)	Max.	Min.	(,,,,,),,,,	
F0303T-W2	2.2	2026	3.3	75	8	60	
F0305T-W2	3.3	3.0-3.0	5	50	5	60	
F0505T-W2	5	4.5-5.5	5	50	5	64	
F0509T-W2			9	28	3	65	
F0512T-W2			12	21	2	67	
F0515T-W2			15	17	2	66	
E0505T-W2			±5	±25	±3	64	
E0509T-W2			±9	±14	±2	65	
E0512T-W2			±12	±10.5	±1	67	
E0515T-W2			±15	±8.5	±1	66	
F1205T-W2			5	50	5	65	
F1212T-W2			12	21	2	63	
F1215T-W2			15	17	2	64	
E1205T-W2	12	10.8-13.2	±5	±25	±3	65	
E1209T-W2			±9	±14	±2	64	
E1212T-W2]		±12	±10.5	±1	63	
E1215T-W2			±15	±8.5	±1	64	

COMMON SPECIFICATIONS

Item	Test Conditions	Min.	Typ.	Max.	Units		
Storage humidity				95	%		
Operating temperature		-40		85			
Storage temperature		-55		125			
Temp. rise at full load			15	25	°C		
Lead temperature	1.5mm from case for 10 seconds			300			
Cooling		Free air convection					
Package material		Epoxy Resin(UL94-V0)					
Short circuit protection*				1	s		
MTBF		3500			k hours		
Weight			1.71		g		
*Supply voltage must be discontinued at the end of abort aircuit duration							

*Supply voltage must be discontinued at the end of short circuit duration.

ISOLATION SPECIFICATIONS							
Item	Test Conditions	Min.	Тур.	Max.	Units		
Isolation voltage	Tested for 1 minute and 1mA max	3000			VDC		
Isolation resistance	Test at 500VDC	1000			MΩ		

OUTPUT SPECIFI	CATIONS					
Item	Test Conditions	Min.	Тур.	Max.	Units	
Output power				0.25	W	
Line regulation	For Vin change of ±1%(3.3V output)			±1.5		
	For Vin change of ±1%(Others output)			±1.2		
	10% to 100% load (3.3V output)		15	20		
	10% to 100% load (5V output)		12.8	15	%	
Load regulation	10% to 100% load (9V output)		8.3	10		
	10% to 100% load (12V output)		6.8	10		
	10% to 100% load (15V output)		6.3	10		
Output voltage accuracy		See tolerance envelope gr			e graph	
Temperature drift	100% full load			±0.03	%/°C	
Output ripple &Noise*	20MHz Bandwidth		50	75	mVp-p	
Switching frequency	Full load, nominal input		100		kHz	
*Test ripple and noise by "parallel cable" method. See detailed operation instructions at Testing of Power						

*Test ripple and noise by "parallel cable" method. See detailed operation instructions at Testing of Power Converter section, application notes.

RECOMMENDED REFLOW SOLDERING PROFILE



APPLICATION NOTE

1) Requirement on output load

To ensure this module can operate efficiently and reliably, During operation, the minimum output load *could not be less than 10% of the full load*. If the actual output power is very small, please connect a resistor with proper resistance at the output end in parallel to increase the load.

2) Recommended testing circuit

If you want to further decrease the input/output ripple, an "LC" filtering network may be connected to the input and output ends of the DC/DC converter, see (Figure 1).

It should also be noted that the inductance and the frequency of the "LC" filtering network should be staggered with the DC/DC frequency to avoid mutual interference. However, the capacitance of the output filter capacitor must be proper. If the capacitance is too big, a startup problem might arise. It's not recommended to connect any external capacitor in the application field.

3) Output Voltage Regulation and Over-voltage Protection Circuit

The simplest device for output voltage regulation, over-voltage and over-current protection is a linear voltage regulator with overheat protection that is connected to the input or output end in series (Figure2).

4) Overload Protection

Under normal operating conditions, the output circuit of these products has no protection against overload. The simplest method is to connect a self-recovery fuse in series at the input end or add a circuit breaker to the circuit.

5) No parallel connection or plug and play

TYPICAL CHARACTERISTICS





RECOMMENDED CIRCUIT





OUTLINE DIMENSIONS & FOOTPRINT DETAILS



Note:

1. Operation under minimum load will not damage the converter; However, they may not meet all specification listed, and that will reduce the life of product.

- 2. All specifications measured at Ta=25°C, humidity<75%, nominal input voltage and rated output load unless otherwise specified.
- 3. Only typical models listed, other models may be different, please contact our technical person for more details.

4. In this datasheet, all the test methods of indications are based on corporate standards.