

CHIP ANTENNA


Page 1 of 3

RCA-W1A0-1204-Z-002

ELECTRICAL SPECIFICATION

PARAMETERS	VALUE	UNIT
Center Frequency	433	MHz
Bandwidth, typ	28	MHz
Peak Gain, typ	0.83	dBi
Return Loss, min	6.5	dB
Polarization	Linear	-
Azimuth Beamwidth	Omni-directional	-
Power, max	1	W
Impedance	50	Ω
Operating Temperature Range	-40 ~ +105	°C
Termination	Ni / Sn (Environmentally-Friendly Leadless)	-

■ MECHANICAL SPECIFICATION






CHIP ANTENNA

Page 2 of 3


RCA-W1A0-1204-Z-002

EVALUATION BOARD



Unit: mm

RECOMMENDED SOLDERING PATTERN



Unit: mm




CHIP ANTENNA

RCA-W1A0-1204-Z-002

FREQUENCY CHARACTERISTICS


Return Loss




Marker data

- 1. 420MHz, -6.5dB
- 433MHz, -17dB
 448MHz, -6.5dB

RADIATION PATTERN



Evaluation board and XYZ direction



Frequency= 433 MHz Max gain = 0.83 dBi, at (150,330)

MEG (mean effective gain)= -4.84 dBi Directivity (dB) = 6.41 Efficiency = -5.57dB, 27.72 %

APPROVAL

RALTRON	
DRAWN BY:	AR, August 15, 2018
APPROVED BY:	CP, August 15, 2018
REVISION:	A, Initial Release

Raltron Electronics / RAMI Technology USA, LLC, including its affiliates, employees, agents and other persons acting on its behalf (collectively Raltron/RAMI Tech), disclaim any and all liability for any errors or inaccuracies contained in this data sheet. While Raltron/RAMI Tech has made every reasonable effort ensure the accuracy of all product information, specifications and data contained herein, Raltron/RAMI Tech does not guarantee that the information is accurate, reliable or current. The product information is provided only for reference purposes only and is subject to change, correction or revision, at any time without notice. Raltron/RAMI Tech does not assume any liability arising out of an application or use of any product described herein and disclaims any warranties expressed or implied. The user of products in such applications shall assume all risks of such use and will agree to hold Raltron/RAMI Tech, harmless against all damages.

Copyright © 2016, Raltron Electronics / RAMI Technology USA, LLC. All rights reserved. No part of this document may be reproduced in any form without the prior written permission of Raltron Electronics / RAMI Technology USA, LLC.